

Übung VKE und Status

U	E1.0	VKE	Status	VKE	Status	VKE	Status	VKE	Status
U	E1.1	...	1	...	1	...	0	...	0
=	A12.0

O	E1.6	VKE	Status	VKE	Status	VKE	Status	VKE	Status
O	E1.7	...	1	...	0	...	1	...	0
=	A4.1

U	E12.0	VKE	Status	VKE	Status	VKE	Status	VKE	Status
UN	M10.0	...	1	...	1	...	0	...	0
=	M17.1

ON	M200.0	VKE	Status	VKE	Status	VKE	Status	VKE	Status
ON	A12.1	...	1	...	1	...	0	...	0
=	A18.2

O	E0.0	VKE	Status	VKE	Status	VKE	Status	VKE	Status
ON	E0.1	...	1	...	1	...	0	...	0
U	E0.2	...	1	...	0	...	1	...	0
=	A100.0

ON	M200.0	VKE	Status	VKE	Status	VKE	Status	VKE	Status
ON	A12.1	...	1	...	1	...	0	...	0
NOT		
=	A1.2

U	M0.0	VKE	Status	VKE	Status
SET		...	1	...	0
=	A17.2

U	M0.1	VKE	Status	VKE	Status
CLR		...	1	...	0
=	A17.2

Lösung Übung VKE und Status

U	E1.0	VKE	Status	VKE	Status	VKE	Status	VKE	Status
U	E1.1	1	1	1	1	0	0	0	0
=	A12.0	1	1	0	0	0	0	0	0

O	E1.6	VKE	Status	VKE	Status	VKE	Status	VKE	Status
O	E1.7	1	1	0	0	1	1	0	0
=	A4.1	1	1	1	1	1	0	0	0

U	E12.0	VKE	Status	VKE	Status	VKE	Status	VKE	Status
UN	M10.0	1	1	1	1	0	0	0	0
=	M17.1	0	1	1	0	0	1	0	0

ON	M200.0	VKE	Status	VKE	Status	VKE	Status	VKE	Status
ON	A12.1	0	1	0	1	1	0	1	0
=	A18.2	0	1	1	0	1	1	1	0

O	E0.0	VKE	Status	VKE	Status	VKE	Status	VKE	Status
ON	E0.1	1	1	1	1	0	0	1	0
U	E0.2	1	1	0	0	0	1	0	0
=	A100.0	1	1	0	0	0	0	0	0

ON	M200.0	VKE	Status	VKE	Status	VKE	Status	VKE	Status
ON	A12.1	0	1	0	1	1	0	1	0
NOT		1		0		0		0	
=	A1.2	1	1	0	0	0	0	0	0

U	M0.0	VKE	Status	VKE	Status
SET		1	1	0	0
=	A17.2	1	1	1	1

U	M0.1	VKE	Status	VKE	Status
CLR		1	1	0	0
=	A17.2	0	0	0	0